


75486-39 TOMA R-TV/SAT UNICA / TOMADA R-TV+SAT ÚNICA / PRISE R-TV+SAT UNIQUE / R-TV+SAT SOCKET-OUTLET SINGLE

75487-39 TOMA R-TV/SAT INTERMEDIA / TOMADA R-TV+SAT INTERMÉDIA / PRISE R-TV+SAT INTERMÉDAIRE / R-TV+SAT SOCKET-OUTLET INTERMEDIATE

75488-39 TOMA R-TV/SAT FINAL / TOMADA R-TV+SAT FINAL / PRISE R-TV+SAT FINALE / R-TV+SAT SOCKET-OUTLET FINAL


CARACTERÍSTICAS TÉCNICAS - CARACTERÍSTICAS TÉCNICAS - INFORMATIONS TECHNIQUES - TECHNICAL SPECIFICATIONS



75486-39

75487-39

75488-39



27097-3.

28097-3.

31097-3.

75097-3.

82097-3.

88097-3.

Art.		75487-39		75488-39		75486-39	
		Intermedia/Intermédia/ Intermédiaire/Intermediate		Final/Final/Finale/Final		Única/Única/Unica/Single	
Máx. tomas por línea Max. tomadas por linha Nombre de prises par ligne Max. sockets per line		3		1		1	
Pérdidas (dB) Perdas (db) Fuites (dB) Losses (dB)	Inserción Inserção Insertion Insertion	R-TV	3,5	-		-	
		SAT	5				
	Derivación Derivação Dérivation Derivation	R-TV	8,5	4		0,6	
		SAT	10	5		1,5	
Aislamiento TV-R (dB) Isolamento TV-R (dB) Isolement TV-R (dB) Isolation TV-R (dB)		>25		>10		>10	
Blindaje (dB) Blindagem (dB) Blindage (dB) Shielding (dB)				>75			
Impedancia (Ω) Impedância (Ω) Impédance (Ω) Impedance (Ω)				75			
Conectores de salida Conectores de saída Connecteurs de sortie Output connectors		IEC 9,5 mm Ø		MACHO/MACHO/MÂLE/MALE R-TV			
				HEMBRA/FÊMEA/FEMELLE/FEMALE SAT			
Banda de frecuencia Banda de frequência Bande de fréquence Frequency band		R-TV		5-862 MHz			
		SAT		950-2150 MHz			

INSTALACIÓN - INSTALAÇÃO - MONTAGE - INSTALLATION

