

Eastbrook

INSTRUCTION MANUAL for WI-FI ON OFF SPUR SWITCH

Compatible with Alexa & Google Assistant



Box contents : 1 x Wi-Fi Spur unit, 2 x retaining screws

SPECIFICATION WIFI CONTROLLED SWITCHED FUSED SPUR			
CODE	41.0799	NAME	WIFI CONTROLLED SWITCHED FUSED SPUR
COLOUR	WHITE	FUNCTION	TUYA SMART LIFE APP CONTROL
INPUT	220/240V AC	COMPATABLE WITH	ALEXA & GOOGLE ASSISTANT
MAINS FREQUENCY	50Hz/60Hz	PROGRAMMABLE	PROGRAMMED (ON and OFF)
AMBIEN T TEMP	-20C – 45C	RATED CURRENT	13AMP
ROCKER SWITCH	2POLE	SWITCHED RATED POWER 13AMP 220/240VAC	MAX 3000W RESISTIVE FOLLOWING MAX LOAD 1000W HALOGEN, INCANDESCENT 100W COMPACT FLUORESCENT 500W LED FLUORESCENT NOT SUITABLE DISCHARGE LIGHT
ELECTRICAL CLASS	II		
PACKING SIZE	85*85*37mm	NET WEIGHT	133g
MINIMUM DEPTH WALL BOX	25MM	BOOST TIME	MULTIPLE SELECT HOURS
WIFI SPECIFICATION	2.4GHZ	FREQUENCY RANGE	2.4 – 2.48GHZ

These instructions are for guidance only Please read before installation and retain for future reference

General safety instructions

- Before commencing the installation ensure the mains supply to the Wi-Fi spur switch is switched off and the circuit supply fuses are removed or the circuit breaker is locked off.
- This unit should be fitted by a qualified electrician adhering to the local regulations and guidance covering the installation.
- The spur is designed to fit a 1gang 25mm deep (min) back box.
- The Spur can be connected into a ring main circuit if required the terminals are large enough to accept 2x2.5mm conductors. An earth loop in/out terminal is provided if required.
- An earth loop through connector is supplied if required.
- If the unit is installed in a metal back box, earthing to the back box is required.
- Connect the supply to terminals marked L IN (brown/red cable) & N IN (blue/black cable).
- Connect the load to L out & N out.
- The load cable can be fed through the cable exit and secured with cable clamp.
- You are advised at every stage of the installation to double check all electrical connections you have made. After completing the installation, there are electrical test that should be carried out and specified in the wiring Regulations BS7671

Operation

- This is a very simple app to programme and to control the fused Spur from anywhere via the internet.
- You will need to down load the TUYA SMART LIFE app on to you phone or tablet.
- You will then need to register by following the instructions on the screen, select the icon. (power switch other) and it will ask you to configure the gateway.
- You will need to power up the switched spur as close to the router and mobile/tablet press the round power button for 3 seconds and confirm the blue Wi-Fi indicator is rapidly blinking.
- Enter your Wi-fi password and the process of pairing and connecting will take place, once connected, wifi blue light will be always light on, if not succeed, the blue light will be always blinking.

Power button

Turn power on or off by pressing power button.

Warranty

This product has one year (12 months) manufacturer's warranty in respect of defective materials and subject to installation being carried out by a qualified electrician in accordance of good practice.



This marking indicates that this product should not be disposed with other household wastes throughout the EU. To prevent possible harm to the environment or human health from uncontrolled waste disposal, recycle it responsibly to promote the sustainable reuse of material resources. To return your used device, please use the return and collection systems or contact the retailer where the product was purchased. They can take this product for environmental safe recycling.

The device can be programmed by selecting time button

- You can set scheduled times by selecting timer button and then press Add, This allows you to set the on time and then an option if you want it to repeat daily and select "ON" and press save.
- Then press add schedule and enter OFF time and repeat daily if required and select "OFF" and press save. Repeat as above as required if more scheduled times are required for daily or weekend operation.

Count down timer

Just select start hour and minutes for counting down.



Android or iOS App
Scan QR Code to download App

Connect to Alexa or Google Assistant

- Open Alexa app or Google Assistant
- Open ,more and select Add a Device



Eastbrook Road, Gloucester GL4 3DB

Technical Helpline : 01452 317890 Email : technical@eastbrookco.com Mon-Fri / 8am-5pm