


# UPS – Extended Runtime Battery Pack

Increase the on-battery runtime for UPS systems by adding additional external battery packs to the UPS. Each battery pack matches specific UPS models. Battery Packs use 2U or 3U of rack-mount space and should be placed adjacent to the supported UPS.



Rear Panel View



1. DC connector : connects to either UPS or 2nd battery box
2. DC breaker: Battery over-current protection breaker

## ORDERING INFORMATION

Part Number	Description	Shipping Weight lb (kg)
VXBP1	Use with VL1500x/VL2000x UPS; 2U; 18.9"D (481 mm); Black Dims: 3.5"H x 17.2"W x 18.9"D (89 mm x 437 mm x 480 mm) Battery: (8) 12V 9AH / 48VDC	74.6 (33.8)
VXBP2	Use with VL2000x/VL3000x UPS; 2U; 23.6"D (600 mm); Black Dims: 3.5"H x 17.2"W x 23.6"D (89 mm x 437 mm x 600 mm) Battery: (12) 12V 9AH / 72VDC	104.4 (47.4)
VXBP3	Use with VL5000x UPS; 2U; 23.6"D (600 mm); Black Dims: 3.5"H x 17.2"W x 23.6"D (89 mm x 437 mm x 600 mm) Battery: (12) 12V 580W at 5 mi / 72VDC	110.4 (50.1)
VXBP4	Use with VD1500x UPS; 2U; 18.9"D (481 mm); Black Dims: 3.5"H x 17.2"W x 18.9"D (89 mm x 437 mm x 480 mm) Battery: (6) 12V 9AH / 36VDC	58.1 (25.2)
VXBP5	Use with VD1500x UPS; 2U; 23.6"D (600 mm); Black Dims: 3.5"H x 17.2"W x 23.6"D (89 mm x 437 mm x 600 mm) Battery: (12) 12V 9AH / 36VDC	104.4 (50.1)
VXBP6	Use with VD2000x UPS; 2U; 18.9"D (481 mm); Black Dims: 3.5"H x 17.2"W x 18.9"D (89 mm x 437 mm x 480 mm) Battery: (8) 12V 9AH / 48VDC	74.6 (33.8)
VXBP7	Use with VD3000x UPS; 2U; 23.6"D (600 mm); Black Dims: 3.5"H x 17.2"W x 23.6"D (89 mm x 437 mm x 600 mm) Battery: (12) 12V 9AH / 72VDC	104. (47.4)
VXBP8	Use with VD5000x/VD6000x/VD10kx UPS; 2U; 27.4"D (696 mm); Black Dims: 3.5"H x 17.2"W x 27.4"D (89 mm x 437 mm x 696 mm) Battery: (20) 12V 5AH	120.0 (54.4)
VXBP9	Use with VD5000x/VD6000x/VD10kx UPS; 3U; 27.4"D (696 mm); Black Dims: 5.2"H x 17.2"W x 27.4"D (132 mm x 437 mm x 696 mm) Battery: (20) 12V 580W	160.0 (72.6)

## Battery Runtimes as a Percentage of Full Load\*

Battery P/N	UPS P/N	Capacity (Watts)	Internal		(1) Battery Pack		(2) Battery Packs		(3) Battery Packs		(4) Battery Packs		(5) Battery Packs		(6) Battery Packs		(7) Battery Packs	
			50%	100%	50%	100%	50%	100%	50%	100%	50%	100%	50%	100%	50%	100%	50%	100%
			VXBP1	VL1500A	1350	12	4	53	22	102	42	N/A	N/A	N/A	N/A	N/A	N/A	N/A
	VL2000A	1800	12	4	50	20	97	40	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A
VXBP2	VL2200A	2000	12	4	54	22	104	43	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A
	VL3000A	2700	12	4	50	20	97	40	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A
	VL3000A-1	2700	12	4	50	20	97	40	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A
	VL3000B	2700	8	3	34	20	66	38	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A
VXBP3	VL5000B	4500	5	2	24	14	45	27	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A
	VL5000B-1	4500	5	2	24	14	45	27	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A
VXBP4	VD1500A	1450	10	3	42	17	84	33	120	51	157	72	199	93	244	112	89	128
	VD1500B	1450	10	3	42	17	84	33	120	51	157	72	199	93	244	112	89	128
VXBP5	VD1500A	1450	10	3	84	33	157	72	244	122	339	146	N/A	N/A	N/A	N/A	N/A	N/A
	VD1500B	1450	10	3	84	33	157	72	244	112	339	146	449	189	523	233	N/A	N/A
VXBP6	VD2000A	1930	10	3	42	17	84	33	121	51	157	72	200	93	244	112	289	128
	VD2000B	1930	10	3	42	17	84	33	121	51	157	72	200	93	244	112	290	128
VXBP7	VD3000A	2880	10	3	42	17	84	33	121	52	158	79	201	94	246	112	292	129
	VD3000B	2880	10	3	42	17	84	33	121	52	158	73	201	94	246	112	292	129
VXBP8	VD5000B	5000	N/A	N/A	21	7	49	20	81	33	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A
	VD6000B	6000	N/A	N/A	15	5	38	15	62	27	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A
	VD10KB	10000	N/A	N/A	7	2	20	7	33	13	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A
VXBP9	VD5000B	5000	N/A	N/A	37	15	86	36	129	58	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A
	VD6000B	6000	N/A	N/A	29	12	66	29	107	47	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A
	VD10KB	10000	N/A	N/A	15	6	36	15	58	25	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A

\*NOTES: Runtimes are shown in minutes and will vary based on battery condition, age, cycles, and ambient temperature. Match batteries to specific UPS. Maximum number of batteries varies depending on battery and UPS model. Maximum of two battery packs with UPS Models VLxxxx. Maximum of seven battery packs with Models VD1500A, VD2000A and VD3000A. Maximum of five battery packs when using VXBP5 with VD1500A. Maximum of eight battery packs for VD1500B, VD2000B and VD3000B. Maximum of six battery packs when using VXBP5 with VD1500B. Maximum of three battery packs with UPS Models VD5000B, VD6000B and VD10KB.

**United States**  
Simi Valley, CA  
800-834-4969  
**Canada**  
Toronto, Ontario, Canada  
+905-850-7770

**Europe**  
Buckinghamshire, UK  
+441628 524834

**Middle East & Africa**  
Dubai, UAE  
+971-4-2602125  
  
Doha, Qatar  
+974-4-267422

**Latin America**  
+52-55-5203-7525  
Toll Free within Mexico  
800-201-7592  
chatsworth.com.co

**Asia Pacific**  
+86 21 6880-0266  
chatsworth.com.cn

